

## Seicane S166221 2005-2011 Toyota YARIS aftermarket radio dvd gps stereo upgrade installation replacement instruction

Seicane S166221 2005-2011 Toyota YARIS car radio after installation



## Some tips before the installation:


- 1. Please disconnect the power before the installation.
- 2. Please prepare a lever and a screwdriver before the removal and the installation.
- 3. Please keep all the separate parts from the car. Please take great care of the dashboard to avoid scratching it during its detachment and installation. Please keep handy any parts from the car and make use of all the original screws from the car as much as possible. so each related part of the unit can be fixed securely.
- 4. For your convenience, here's the recommended tools for removal and installation from Seicane, please check for more details:

http://www.seicane.com/car-dvd-dismantling-device-srd-400



## 2005-2011 Toyota YARIS car radio installation guide

1.Using a plastic tool, carefully pry out the trim panels that surround the climate controls. And set them aside without unplugging connectors.



2.Pull out the panel with your hands with medium force.



3. Unscrew the four 10mm bolts holding the radio in place.





4. When the screws are out, pull the radio out of the dash.



5. Disconnect the harness and antenna plug at the back of the original car radio.



- 6. Check all the accessories for the new Seicane car radio.
- 7. Connect the harnesses to the back of the new Seicane car radio.
- 8. Connect the Seicane car radio to your original car radio 's plugs.
- 9. Turn on the new Seicane radio to have a careful check if everything works well. If it doesn't, please check whether all the cables are connected correctly.
- 10.Put the new Seicane radio into the dash.
- 11. Put everything into their original place. All the installation is done.

## Please note:

We suggest you arrange a professional to install it. If you have any questions about installation, please send us photos about your original car's plugs, we can make a wiring diagram for your car.